ELECTRONIC VALVE SPECIFICATIONS


SPECIFICATION MOA/CV2479, ISSUE 1B, DATED 19th July, 1964. AMENDMENT NO. 1

Page 4 Cancel (but do not remove) existing Page 4 and substitute new Page 4, dated 1st October, 1964, attached hereto.

T.V.C. for R.R.E.


November, 1964. NM.190472

FIG. 2



NOISE DIODE OUTLINE DRAWING (THIRD ANGLE PROJECTION)

FIG. 3



OUTLINE DRAWING OF APPROVED MOUNT

DIMENSIONS IN INCHES

CV 2479 / IB /4

IST OCTOBER 1964

VALVE ELECTRONIC CV2479


Specification MOA/CV2479	SECURITY		
Issue 1B Dated 19th July 1964	<u>Specification</u>	<u>Valve</u>	
To be used in conjunction with BS448, BS1409 and K1001, excluding clauses 5.2, 5.3, 5.5, 5.7, 5.9	UNCLASSIFIED	UNCLASSIFIED	

✓ Indicates change						
TYPE OF VALVE: Noise Tube, Gas Filled CATHODE: Indirectly heated ENVELOPE: Glass PROTOTYPE: VX1036	, Low Current	MARKING See K1001/4 Cathode connection indicated by white spot on base				
ABSOLUTE NON-SIMULTANEOUS RA (Not for inspection purp	-	BASE AND CONNECTIONS See Drawing Page 4				
Heater Voltage (V) Heater Current (A) Max. Striking Voltage (in mount) (V) Normal Voltage Drop across tube (V) Preferred Operating Current (mA) Min. Operating Current (mA) Min. Series Resistance (2) Nominal noise power available (dB) Nominal noise power output charge with current (dB/mA) Useful frequency range (Mc/s)	6.3 1.0 1,150 C 50 A 35 25 50 1,500 15.25 B 0.03 9,000 to 18,000					

NOTES

- A. The value quoted is that which is obtained with $I_1 = 35mA$. In order to ensure adequate performance of the tube the circuit and anotes given on page 2 may be used. It is essential that the energy available for striking the tube exceeds the minimum value of 2×10^{-3} joules.
- B. Given as a reference to thermal noise at 17°C. The figure quoted is that which is obtained with the tube fitted in a mount conforming to the dimensions given on Fig. 3, and which is terminated with a matched load.
- C. In order to avoid the presence of High d.c. voltages a striking circuit as given in Fig. 1 may be used.

(222380)



STRIKING CIRCUIT

NOTES

- V1. This should have a value not less than 120 volts. The supply must not be inductive or striking may be difficult. If a relay winding is used in series with this supply, it must be damped or by-passed to prevent escillation.
- V2. This can be common with V1 if a suitable ratio is chosen for transformer T. If a higher voltage is available this will enable a lower ratio to be used for transformer T.
- T. This transfermer should be capable of producing a half sine-wave pulse with a base width of 20 usecs. The transfermer should have a step up ratio of 1500 on open circuit.
- R1. This should be chosen to make Ia = 35 mA with a selected value of V1.
- C. This determines the energy available for striking the tube and should have a value such that: -

 $W = \frac{1}{2} CV2^2$ is not less than 2×10^{-3} jeules

R2. It is convenient to make CR2 = 1 sec approximately.

TESTS

To be performed in addition to those applicable in K1001


Test shall be performed in the specification order unless otherwise agreed with the inspecting authority.

	Test condition - unless otherwise specified Vf = 6.3V Ia = 35 mA										
K1001 Ref.	Test	Test Conditions	AQL S	Insp. level	Sym- bol	Limits		TY24-			
						Min.	Max.	Units			
	Filament Current	Note 1		100%	If	0.9	1.1	A			
	v.s.w.r. (1)	F = 9375 ± 25 Nc/s Note 2		100%		-	1.06	Ratio			
	v.s.w.r. (2)	F = Over the range 9025 to 9726 Mc/s Note 2		10,5		_	1.25	Ratio			
	Noise Output	Note 3		10%		15.0	15•5	đВ			

NOTES

- 1. The heater voltage should be applied 30 seconds before performing the test.
- 2. The diode is inserted in the approved 15° E-plane mount in No. WG16 waveguide which is terminated in a matched load, and the mount is screw tuned with diode struck to give a v.s.w.r. at 9375 Mc/s of less than 1.03.
- 3. The diode is inserted in the approved 15° E-plane mount in No. WG16 waveguide which is terminated in a matched load.

CV2479/1B/3






FIG. 3
OUTLINE DRAWING OF APPROVED MOUNT

CV 2479/1B/4