




T.			U_f	I_f	Cl.	U_a	U_{g2}	U_{g3}	U_{g1}	I_a	I_{g2}	I_{g1}	$U_{g1 \approx}$	P_{dr}	P_o	P_{g2}	P_a
			V	A		V	V	V	V	mA	mA	mA	V	mW	W	W	W
7054	RCA	1	$13,5 \pm 1,5$	0,275	C-Tgr	200 250 300 300	115 145 175 175	0 0 0 0	-7 -9 -12 -50	14,5 20 26 33	3 4,1 5,5 5,5	0,6 0,85 1 3	9 11 16 maximum	10 12 15	1,5 2,7 4	1	5
					stat.	250	150	0	-50	19	3,5	3,5					

$R_k = 120\Omega; S = 11,5mA/V; R_f = 0,1M\Omega$

C_{g1}	C_a	$C_{g1/a}$	vide *5
pF	pF	pF	
10,2	3,5	0,063	



7054

