Specification MAP/CV64/Issue 6 Dated 14.1.49	SECURITY					
To be read in conjunction with K1001 ignoring clauses: - 5.2, 5.3, 5.8.	Specification RESTRICTED	<u>Valve</u> UNCLASSIFIED				
→ Indicates a change						

Indicates a change									
TYPE OF VALVE - Magnetron CATHODE - Indirectly Heated ENVELOPE - Copper			MARKING See K1001/4 PACKING See K1005						
RATING		Note	BASE None						
Filament Voltage (V) Filament Current (A) Nominal Operating Frequency (Mc/s) Max. Mean Power Input (W)	6.0 1.25 3300 350	A	DIMENSIONS & CONNECTIONS See drawing on page 3						
TYPICAL OPERATING CONDITIONS Peak Anode Voltage (kV) Peak Anode Current (A) Field Strength (gauss) Peak Power Output (kW)	13.0 10.0 1350 40	A A A							

NOTE

When operating under these conditions the magnetron must be air-cooled such that the temperature of the block does not exceed 140°C.

CV64 To be perform

TESTS To be performed in addition to those applicable in K1001

	Test Conditions		Test		Limits		No.	77 - 4	
					Min.	Max.	Tested	Hotes	
	Field Strength (gauss)	Vh	Peak Ia (A)						
a	0	6.0	0	Ih	(A)	1.0	1.5	100%	
ъ	1350 <u>+</u> 25	6.0	10	Peak Va	(kV)	12.0	14.5	100%	2
c	1350 <u>+</u> 25	6.0	10	Output Freque	ncy (Mc/s)	3 288	3312	100%	2 & 3
đ	1350 ± ²⁵	6.0	10	Efficiency		20%	-	100%	2 &
e	1350 <u>+</u> 25	6	10	Frequency Pul	ling (Mc/s)	_	10	T/A	2 & 5
£	COLD IMPR A signal shall be shown in standing of the va								

NOTES

- 1 For the above tests the temperature of the magnetron block shall not exceed 140°C.
- 2 Test to be carried out with the valve feeding into an output circuit, the dimensions of which are given in Fig.2. The impedance of the line beyond DD' on the drawing shall be 78 ohms. The matching shall be adjusted for maximum power out when the centre line of the matching slug shall lie between the planes BB' and CC'. Modulation conditions shall be:-

Pulse length 1 µsec. Repetition frequency 2500 p.p.s.

- 3 If in test (c) there is an unwanted mode, as shown by a continuous base line on the oscilloscope, the valve shall be deloaded to 80% of its maximum power, when the continuous base line shall have disappeared.
- 4 If a valve which has once passed test (d) is re-tested for any reason, it shall be considered satisfactory if the measured output on re-test is within + 10% of the original value.
- 5 Frequency pulling shall be measured by varying the phase of a standing wave of ratio 1.5:1 through 180°, using the matching slug position found for maximum power.

FIG I

NOTES FOR USERS

1. THE DIA OF THE CIRCUIT TUBE OVER THIS
LENGTH MUST NOT BE LESS THAN 0.667"

2. THE MINIMUM RADIATOR HOUSING WIDTH

MUST BE '625"

3. THE NORMAL MAGNET AIR GAP IS 1.496"±0.004"



