MINISTRY OF SUPPLY (D. L. R. D. (A)/R. A. E.)

## VALVE ELECTRONIC

CV2354

Specification MOS(A)/CV.2354

Issue 2 Dated 14.9.55

To be read in conjunction with BS448 and K1001
ignoring clauses: 5.2, 5.3 and 5.8

SECURITY

Specification Valve
UNCLASSIFIED

TYPE OF VALVE - Velocity Modulated Tunable Internal ( coaxial line output	MARKING See K. 1001/4						
CATHODE - Indirectly Heated	TOP CAP						
ENVELOPE - Metal/Glass	B.S. 448/CT2						
PROTOTYPE - R. 6015			<del></del>				
RAT ING		BASE					
			Note	1	B. S. 448/B8G		
Heater Voltage Heater Current Max. Resonator Voltage Normal Resonator Voltage Reflector Voltage Range Grid Voltage Range  Max. Resonator Current Min. R.F. Power output		300 275 -50 to -250 0 to -100	C A,B,D B,C B,G,F B	5	Connections  Cathode Internally Connected Grid Heater Grid Heater Internally Connected		
Mechanical Tuning Range  Min. Electronic Tuning Range Max. Reflector Voltage Change	(Mc/s)	4270 to 4760	E	8 TC Metal	Grid Reflector Resonator		
over 10 Mc/s range Mean Reflector Voltage Change over 10 Mc/s range Max. total impedance in reflector to cathode circuit	(V) (∀)			DIMENSIONS See Drawings on pages 4 and 5			
There shall be no appreciable potential difference between heater and cathode.				MOUNTING POSITION Any Note H			

NOTES

See page 2

CV.2354/2/1

## NOTES

- A. Absolute Value.
- B. The voltages quoted in this specification are relative to cathode.

  The valve is normally operated with the resonator at earth potential.
- C. It is preferable that the resonator voltage is not switched on until at least 60 seconds after the heater.
- D. The temperature of the valve envelope should not at any point exceed 200°C, nor should that of the external metal parts exceed 150°C. Forced air cooling is not normally necessary.
- E. Measured at half-power points.
- F. If a high impedance reflector supply is used, the circuit must include a diode to prevent the reflector reaching a potential more positive than the cathode.
- G. The reflector voltage required depends on the frequency and mode of oscillation. Over the specified frequency range the specified power is obtained at a voltage within the limits stated.
- H. The valve is mounted on a waveguide of internal dimensions 2" x 1", terminated by a matched load. A reflecting plunger at the valve end of the waveguide is fixed at a distance from the output probe corresponding to a quarter wavelength at midband (4515 Mc/s).

CV.2354/2/2


## To be performed in addition to those applicable in K.1001

Test Conditions			Tests	Limits		No.	Note			
			16303	Min.	Max.	Tested				
	Vh (V)	vg (v)	Vres. (V)	∀ref. (V)	Freq. (Mc/s)					
а	6, 3	٥	Q	0	0	In (4)	0.8	1.0	100%	1
ъ	6.3	0	275	Adjust for maxe power	4270	(1) Ia (mA) (2) Vr (V) (3) Ir (µA) (4) Power (mW) output	-50 -10	70 -250 10 300	1 00% 1 00% 1 00% 1 00%	1,4
C	6,3	0	275	Adjust Vr less -ve for half power; Note value (Vr1) Adjust Vr more -ve for half power; Note value (Vr2)	Note value (f1)	(1)f1-f (Mo/s) (2)f-f2 (Mo/s) (3) <u>f1-f2</u> (Mo/s/N Vr2-Vr1	5	2. 2	100% 100% 100%	1,2,
đ	d As test b		4760	As test b						
	e As test c		4760	As test c						
f	f As test b		4515	As test b						
g	g As test c		4515	As test c						
h	5•8	0	275	Adjust for max. power	Any value	Ia	obse val		100%	1
j	<b>6</b> , 8	0	275	Re-adjust for max. power	•	Change in Ia from value in test (h)	_	15	1 00%	1,2
k				Re-test after 28 ng period			*			
Ш	As test b		4515	As	test	ъ		5		


## NOTES

- 1. The valve shall be run under normal operating conditions for a minimum period of 10 minutes before carrying out tests (a) to (k).
- Tests (c), (e), (g) and (j) are to be done with mechanical tuning set as in tests (b), (d), (f) and (h) respectively.
- There shall be no discontinuity in the rate of change of power with reflector voltage between the half power points.
- 4. The frequency shall be adjusted by means of the mechanical tuning with the reflector voltage adjusted simultaneously for maximum power.
- 5. That part of Ir due to the ion current shall not have increased over the original value by more than the expected error of measurement.

CV.2354/2/3



CV.2354/2/4



CV.2354/2/4