MINISTRY OF AVIATION, D.L.R.D./R.A.E.

SPECIFICATION M.O.A./CV.2659	SECUE	UTY
Issue 3 Dated 2.11.59.	SPECIFICATION	VALVE
To be read in conjunction with BS.448, BS.1409 and K.1001.	Unclassified	Unclassified

TYPE OF VALVE: Beam Tetrode for and Blocking Osci				MARKIN See K.100		
CATHODE: Indirectly Heated ENVELOPE: Glass, unmetallis PROTOTYPE: 3D21A	eđ.			<u>Bas</u> B s. 448/	•	
RATINGS (All limiting values ar	e absolute)	notes		CONNECT	<u>LONS</u>	
Heater Voltage	() 6.3	A,B	Pin	El	.ectrod	le
Heater Voltage Heater Current Max. Peak Anode Voltage Max. D.C. Anode Voltage Max. Screen Grid Voltage Max. Peak Negative Control Grid Voltage Max. Peak Positive Control Grid Voltage Max. Anode Dissipation Max. Control Grid Dissipation Max. Screen Dissipation Max. Heater-Cathode Voltage Max. Pulse Length (Kax. Pulse Length Len	7) 3.5 850 7) 500 87) 220 87) 0.5 87) 4150 8) 4150 8) 10	A,BC A,C D,F F D	1 2 3 4 5 6 7 8 T.C.	DIMENSI See K.1001	cion d d d ion rid CONS	
Anode Current (m Screen Current (m Mutual Conductance (mA/	A) 2.5	H H H	Dime	ension (mm)	Min.	Max.
Max. Acceleration (continuous operation) (Max. Shock (short duration) (g) 1.0 500			B MOUNTING F	OSITIO	46 <u>M</u>
CAPACITANCES (pF	Σ			Vertic	al.	
C in (nom.) C out (nom.) Ca,g1 (max.)	17 10 1.2					

NOTES

- A. Cathode must be preheated for a minimum of 30 seconds before applying grid pulse,
- B. Heaters parallel-connected.
- C. Heaters series-connected.
- D. Including transients.
- E. With maximum screen voltage of 400 volts and when no transients are present (essentially resistive anode load) a maximum D.C. anode voltage of 4500V D.C. may be applied.
- F. Series resistance must be inserted in the power supply to limit the D.C. short-circuit current to less than 0.5A.
- G. Total pulse length in any 240 μ second period shall not exceed 12 μ seconds.
- H. Measured at Va = 600V D.C. Vg2 = 300V D.C. $Rk = 825\Omega$.

C.V. 2659

Heal Lead Rev. Ano. Sor. Muti Ano. Hig Ope. Peal	Vh (Y) 6.3 TEST DUP A ater Current ater Cathode akage Current, werse Grid Current ode Current cual Conductance ode Current (2) th Voltage Pulse eration	Va (V) 600 TEST CONDITIONS Vhk = ± 100V. Note 1. Va = ¼ kV., Vg2 = 300V. Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = ¼ kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = ¼20V. Vg2 = 800V.	V 65 (V) 3000 AQL %)	SYMBOL Ih Ihk -1gl Ia Ig2 gm Ia	1.5 - - 28 - 4.2	1.7 - 31.5 - 5.2 - NOTE 3	1.9 175 5 35 3 6.2	UNITS A µA µA mA mA/V
Ref. GRO Hea 5.3 Hea Lea Rev. Ano. Scr. Muti Ano. Higgope. Peal	ater Current ater Cathode akage Current. Forse Grid Current ode Current (1) Freen Current cual Conductance ode Current (2) th Voltage Pulse eration	Vhk = ± 100V. Note 1. Va = 4 kV., Vg2 = 300V. Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	%	1006 1006 1006 1006 1006 1006	Ih Ihk -igl Ia Ig2 gm	1.5 - - 28 - 4.2	1.7 - 31.5 - 5.2	1.9 175 5 35 3 6.2	A LIA LIA MA MA/V
Heal Lead Rev. Ano. Sor. Muti Ano. Hig Ope. Peal	ater Current ater Cathode akage Current. Forse Grid Current ode Current (1) Freen Current cual Conductance ode Current (2) th Voltage Pulse eration	Va = 4 kV., Vg2 = 300V. Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	1 1	1006 1006 1006 1006 1006 1006	ink -igl ia ig2 gm	- 28 - 4.2	- 31.5 - 5.2	175 5 35 3 6.2	ILA INA INA INA
5.3 Heal Leal Revi Anor Sor Mutu Anor Peal Peal	ater Cathode skage Current verse Grid Current ode Current (1) reen Current cual Conductance ode Current (2) th Voltage Pulse eration	Va = 4 kV., Vg2 = 300V. Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	1 1	1006 1006 1006 1006 1006 1006	ink -igl ia ig2 gm	- 28 - 4.2	- 31.5 - 5.2	175 5 35 3 6.2	LIA MA MA MA
Leal Rev Anox Sor Muti Anox Higi Ope	skage Current. Perse Grid Current pde Current (1) Preen Current Cual Conductance pde Current (2) th Voltage Pulse pration	Va = 4 kV., Vg2 = 300V. Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	1006 1006 1006 1006 1006	-igl la lg2 gm	28 - 4.2 -	- 5•2	5 35 3 6.2	MA. MA. MA. MA/V
Anores Service Anores A	ode Current cual Conductance ode Current (2) th Voltage Pulse pration	Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	1006 1006 1006 1006	ia ig2 ga	28 - 4.2 -	- 5•2	35 3 6.2	mA. MA.
Ser Muti Ano Higi Ope Peal Peal	reen Current cual Conductance ode Current (2) th Voltage Pulse eration	Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.		1006 1006 1006	Ig2 gn	- 4•2 -	- 5•2	3 6.2	mA mA/V
Ano Hig Ope Peal Peal	cual Conductance ode Current (2) th Voltage Pulse	Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	100% 100%	gm	4 . 2	-	6.2	mA/V
Anor Higi Ope: Peal Peal	ode Current (2) th Voltage Pulse	Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	100%		-	-		
Hig Ope Peal Peal	ch Voltage Pulse eration	Vg1 = -150V. Rk = 0 RL = 2 MΩ Va = 4 kV., Vg2 = 800V. Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	·	la	-		300	μA
Peal Peal Peal	eration	Vg1 = -150V., Vg1 peak pulse volts = +150V. Note 2. Va = 420V. Vg2 = 800V.	-	100%	-		NOTE 3		-
Peal Peal	k Anode Current								
Peal		Vg1 = ~150V. Vg1 peak pulse volts = +150V. Note 4.		100%	Iapk	6•5	-	-	A
	ak Screen Current	As for Peak Anode Current test. Note 4.	-	100%	1g2pk	-	-	4.0	A
Peal	uk Grid Current (1)	As for Peak Anode Current test. Note 4.	. -	100%	Igipk	-	-	2.0	A
	nk Grid Current (2)	As for Peak Anode Current test except that Vg1 Peak pulse volts = +50V. Note 4.	1	100%	Igipk	30	-	-	mÅ
GRO	OUP B			,					
A.III Capa	acitance	Measured on tMc/s bridge in fully shielded holder. Valve unscreened. Note 5.	6.5	ŢĀ.	Cag1 Cin Cout	13 7•5	- 17 10	1.2 21 12.5	pF pF pF
GRO	OUP C								
11.2 Res	onance Search	$Vh = 12.6V_{\odot}, Va = 250V_{\odot},$ $Vg2 = 100V_{\odot}, Vg1 = -10V_{\odot},$ $RL = 2 M_{\odot}.$ Acceleration = 2 g min. Frequency Range = 30-250c/s	6.5	IC	- Va(rms)	-	-	- 500	- mVrms
11.3 Fat	igue	Vh = 6.3V. No other voltages Acceleration = 2.5 g min. Frequency = 170 ± 5 c/s. Note 6.		IA	-	-	-	-	-

K. 1001	TEST	TEST CONDITIONS	AQL	INSP.	SYMBOL		LIMITS		UNIT
Ref.			75	LEVEL		MIN.	30CEY	MAX.	
	Post Fatigue Tests								
5.3	Heater-Cathode	Vhk = * 100V.	6.5		Ihk	-	-	175	114
	Leakage Current	Note 1.							,
	Reverse Grid Current		6.5	-	-Igl	-	-	10	μA
	Mutual Conductance		6.5	-	gm	4.2	5.2	6.2	m& /^
11.4	Shock Test	No voltages.	-	IĀ	-	-	-	-	-
		Hammer angle = 30°. Number of shocks in each							
		direction = 5.							
	Post Shock Tests								
5.3	Heater-Cathode	Vhk = * 100V.	6.5	-	Ihk	<i>'</i> -	-	175	μA
	Leakage Current	Note 1.							
	Reverse Grid Current		6.5	-	-Igl	-	-	10	μA
	Mutual Conductance		6.5	-	gm	4.2	5.2	6.2	mA/
	GROUP D								
AUT /C 7	Life. Note 7.	Va = 3.5kV., Vg2 = 800V.	_	īC	_	_		_	_
AV1/303	Lite. nove /.	Vg1 = -150V., Vg1 peak pulse Volts = +150V.	_	10	_	_			
AVI/5.6	Life Test End Point (500 hours)							
	Peak Anode Current	As for Peak Anode Current in Group A.	6.5	•	Iapk	5.0	-	-	A
	GROUP E								
AIX/2.5	Electrical Retest		_	100%					
	after 28 days holding period.	-							
	Inoperatives.		0.5	_	_	_			_

NOTES

- 1. 100 $k\Omega$ resistance connected in series with Vhk.
- After a minimum pre-heat time of 30 secs. with heater volts only, the valve shall be subjected to the following pulse conditions in the circuit on page 5, Fig. 1.
 A substantially rectangular pulse having a peak amplitude as specified and a duty cycle of not
 - A substantially rectangular pulse having a peak amplitude as specified and a duty cycle of not less than .001 (averaged over a time interval of less than 20 m.secs.) shall be applied to the grid of the valve under test.
- Initial arcing may be tolerated but the valve shall be free from arcing after a period of one minute.
- After a minimum pre-heat time of 30 secs. with heater volts only, the valve shall be subjected to the following pulse conditions in the circuit shown on page 5, Fig. 2.
 A substantially rectangular pulse having a peak amplitude as specified and a duty cycle of not
 - A substantially rectangular pulse having a peak amplitude as specified and a duty cycle of not less than .001 (averaged over a time interval of less than 20 m. secs.) shall be applied to the grid of the valve under test.
- 5. The capacitance connections shall be:-

HP	LP	Ε
6	TC	1,2,4,7,8.
6	1,2,4,7,8.	TC
7C	1,2,4,7,8.	6
		6 1,2,4,7,8.


CV.2659/3/3

C.V. 2659

NOTES (Contd.)

- 6. Valves shall be vibrated in each of the three required planes for not less than 23 hours. Heater switched 1 minute on 3 minutes off. No other voltages applied.
- 7. Valves shall be operated in a suitable circuit under the conditions specified with the \sim following pulse applied.
 - A substantially rectangular pulse having a peak amplitude as specified and a duty cycle of not less than .001 (averaged over a time interval of less than 20 m.secs.) shall be applied to the grid of the valve under test.

CV.2659/3/4



C V. 1659/3/5