## MINISTRY OF SUPPLY - D.L.R.D. (A)/R.A.E.

# VALVE ELECTRONIC CV2872

Specification MOSA/CV2872	SECU	SECURITY			
Issue 3 Dated 17.3.53	Specification	<u>Valve</u>			
To be read in conjunction with K.1001	UNCLASSIFIED	UNCLASSIFIED			

Indicates a change

TYPE OF VALVE - Water Cooled, T	MARKING			
CATHODE - Directly Heated Filament		See K.1001/4. Additional markings required (See Notes B & C)		
ENVELOPE - Metal-glass				Serial No
PROTOTYPE - CAT.9, BW153	Filament Volts			
RATING				DIMENSIONS AND
	Note	CONNECTIONS		
Filament Voltage	(₹)	As marked	A	See drawingson pages 324
Nominal Filament Current	(A)	100		
Max. Anode Voltage	(k∀)	15.0		
Max. Anode Current	(A)	2.0		
Max. Continuous Anode Dissipation	(kW) (A)	18		
Total Emission at 90% Saturation Amplification Factor	12.0 45	D		
Anode Impedance	(Ω)	4.500	D	
Max. Operating Frequency at	(/	7,700		}
Full Ratings	(Mo/s)	3.0		
Max. Operating Frequency at		·		
Reduced Ratings	, , ,			
$(\nabla \mathbf{a} = 9  \mathbf{k} \nabla)$	(Mo/s)	20.0		

## NOTES

- A. In operation, the anode must be surrounded by a suitable jacket to contain the circulating liquid, whose rate of flow should not be less than 4½ gallons per minute. The filament seal and the anode seal require to be cooled, the former with 2 to 3 cu. ft. of air per minute and the latter with 5 to 10 cu. ft. of air per minute.
- B. The marked voltage is defined in test clause "g" on page 2.
- C. It is not essential that the additional marking shall appear within the frame.
- D. Measured at Va = 12.0 kV, Vg = 0.


CV.2872/3/1

# To be performed in addition to those applicable in K1001


	Test Conditions		ons		Limits		No.		
	Vf (A.C)	Va (kV)	Ia (A)	∀g	Test	Min.	Max.	Tested	Notes
	18.5	0	0	0	If (A)	95	105	100%	
ď	18.5	14.0	1.5	Adjust	1) Vg to be actual 2) Ig initially (μA) 3) Ig after conditions have been maintained for 10 mins. (μA)	-	150 100	100% 100% 100%	1
•	18.5	17.0	-		Oscillation officions	69%	-	100%	1&2
đ	18.5	14-0	1.5	Adjust	1) Difference in value between Vg here and as recorded in what 'b' 2) Ig initially (MA) 3) Ig after conditions have been naintained for 10 mans. (MA)	- -	120 100	100% 100% 100%	1
•	18.5	read	1.0	0	μ	40	50	100%	
2	18.5	11.0 13.0	read	-100 0 0	Ra (Ω)	4,000	5,250	160%	
8	Read	Read 450V. applied to anode and grid strapped.  Vf adjusted to give an emission current of 2.0k.		rid l to saion	Recorded Vf & 1.25 (V) (This is the marked voltage).	18.1	19.7	100%	3
h	18.5	4.0	-	See Note 4	Ig (A)	See No	te 4		4

## Nt. 2

- 1. Test 'b', 'c' and 'd' must be performed to the order in which they appear in the test schedule, i.e. test 'b' shall be followed immediately by test 'c' shall be followed immediately by test 'c'.
- 2. The oscillation test shall be performed in a suitable circuit with wavelength of oscillation not greater than 450 metres. The input power shall be approximately 25 kW., and the duration of the best shall be 20 mins. During the test the valve shall be free of flash area and best should be the glass and the output shall be steady.
- 3. This 'marked voltage' is the minimum value 200 12.0A emission at 90% saturation.
- 4. Ig is measured at Vg = 4200, 4300, and 4400 Vol. s respectively, the graphical representation of the results obtained show a consibly linear curve.



CV2872/3/3



CV2872/3/4